

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

Amendments to the Claims:

Claims 2, 5, 8 – 11, 15 – 21, 27 – 42, and 49 – 50 are original. Claims 1, 3 – 4, 6 – 7, and 12 – 14 are currently amended. Claims 23 – 26, and 44 – 48 are previously presented. Claims 22 and 43 are cancelled. Claim 51 is new. No new matter is introduced by these amendments.

5 **Listing of Claims:**

Claim 1 (currently amended): A method for changing a selectable divisor in a programmable frequency divider, the frequency divider comprising a plurality of cascaded cells, the method comprising:

- 10 (a) providing a plurality of divisor signals;
- (b) selectively switching each of the plurality of cells to a divide-by-two or a divide-by-three mode according to the plurality of divisor signals; and
- 15 (c) synchronously resetting at least a part of the plurality of cells in response to a reset signal by returning each cell into a predetermined respective state.

Claim 2 (original): The method of claim 1, wherein step (c) further comprises synchronously resetting all of the plurality of cells.

- 20 Claim 3 (currently amended): The method of claim 1, wherein the method step (e) further comprises step (d):
reloading the plurality of divisor signals to the plurality of cells in response to a reload signal.

- 25 Claim 4 (currently amended): The method of claim 3, wherein step (d) further comprising comprises synchronously reloading the plurality of divisor signals to the plurality of cells.

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

Claim 5 (original): The method of claim 3, wherein the plurality of cells comprises at least one cell having a bypass mode, the method further comprising:

- 5 determining whether to bypass at least a part of the at least one cell having a bypass mode according to the plurality of divisor signals in order to inhibit bypassed cells from performing a frequency-dividing operation.

- 10 Claim 6 (currently amended): The method of claim 5, wherein step [(c)] (d) further comprises synchronously resetting each bypassed cell.

- 15 Claim 7 (currently amended): The method of claim 5, wherein step [(c)] (d) further comprises synchronously resetting the plurality of cells.

- 20 Claim 8 (original): The method of claim 5, wherein the reloading step further comprises synchronously reloading the corresponding divisor signals to the bypassed cells.

- 25 Claim 9 (original): The method of claim 5, wherein the reloading step further comprises synchronously reloading the plurality of divisor signals to the plurality of cells.

- 30 Claim 10 (original): The method of claim 5, further comprising:
utilizing a control circuit coupled to the bypassed cells for providing a reset signal.

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

Claim 11 (original): The method of claim 5, further comprising:
utilizing a control circuit coupled to each of the plurality of cells
for providing a reset signal.

5 Claim 12 (currently amended): The method of claim 11, wherein step [(c)]
(d) further comprises utilizing the control circuit to output the
reset signal to the bypassed cells and a cell having a bypass mode
which is prior to the bypassed cells, the reset signal being output
after the bypassed cells are loaded with the corresponding divisor
10 signals.

Claim 13 (currently amended): The method of claim 5, wherein step [(c)]
(d) further comprises bypassing a cell having a bypass mode
when divisor signals input to the cell and each of its subsequent
15 cells having a bypass mode are logic 0.

Claim 14 (currently amended): A programmable frequency divider for
dividing the frequency of a source signal according to a
selectable divisor which is obtained based on a plurality of
20 divisor signals and outputting a result signal having a divided
frequency, the programmable frequency divider comprising:
at least one cell of a first type being switchable between
divide-by-two and divide-by-three modes having a first input
node (Fi), a second input node (Mi), a third input node (Di), a
25 fourth input node (Rs), a first output node (Fo), and a second
output node (Mo), the third input node (Di) being used for
receiving a corresponding divisor signal, the fourth input node
(Rs) being used for receiving a reset signal from a control

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 circuit to synchronously reset the cell of the first type;
wherein if the programmable frequency divider comprising a
plurality of cells of the first type, the cells of the first type
being cascaded with each other, the first output node (Fo)
being coupled to a first input node (Fi) of a subsequent cell of
the first type, the second input node (Mi) being coupled to a
second output node (Mo) of the subsequent cell of the first
type, a first input node (Fi) of a first cell of the first type
being coupled to the source signal, and a second input node
10 (Mi) of a last cell of the first type being set to logic 1; the
programmable frequency divider synchronously resets all of
the cells of the first type according to the reset signal in order
to selectively switch each cell of the first type to perform a
divide-by-two or divide-by-three operation according to the
15 respective divisor signal after the cell is reset, and the second
output node (Mo) or the first output node (Fo) of the last cell
of the first type outputs the result signal having the divided
frequency.

20 Claim 15 (original) The programmable frequency divider of claim 14
wherein each cell of the first type operates such that:
(a) regardless of the logic level of the second input node (Mi), if
the first output node (Fo) and the third input node (Di) are
both at logic 0, the positive edge of a clock signal of the first
25 input node (Fi) triggers the first output node (Fo) to output a
half frequency signal;
(b) if the second input node (Mi) and the third input node (Di) are
both at logic 1 and the first output node (Fo) is at logic 0, the

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;

- 5 (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and
- 10 (e) if the reset signal received on the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal and, additionally, if the second input node (Mi) is at logic 1, the second output node (Mo) outputs a logic 1 signal.

15 Claim 16 (original): The programmable frequency divider of claim 14 wherein each cell of the first type operates such that:

- (a) regardless of the logic level of the second output node (Mo), if the third input node (Di) is at logic 0, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 20 (b) if the second output node (Mo) and the third input node (Di) are both at logic 1, the positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- 25 (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi), if

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and

- (e) if the reset signal received in the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal; and, additionally, if the second input node (Mi) is at logic 1, the second output node (Mo) outputs a logic 1 signal.

Claim 17 (original): The programmable frequency divider of claim 14 further comprising:

a cell of a second type having a bypass mode and being cascaded to the last cell of the first type, the cell of the second type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (Rs), a fifth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first input node (Fi) being coupled to a first output node (Fo) of the last cell of the first type, the second input node (Mi) being coupled to Vcc, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (Rs) being used for receiving the reset signal to synchronously reset the second cell, the fifth input node (Ci) being used for receiving the last divisor signal, and the second output node (Mo) being coupled to a second input node (Mi) of the last cell of the first type;

wherein the cell of the second type switches to the divide-by-two or the divide-by-three mode according to the divisor signal received on the third input node (Di) after being synchronously reset, and if the last divisor signal received on the fifth input node (Ci) is at a bypass-mode active state, the

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

cell of the second type switches to a bypass mode.

Claim 18 (original): The programmable frequency divider of claim 17 wherein each cell of the second type operates such that:

- 5 (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) and the third input node (Di) are both at logic 0, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 10 (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1, the positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a
- 15 one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi),
- 20 if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal;
- (e) if the reset signal received on the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal;
- 25 and
- (f) if the signal received on the fifth input node (Ci) is at an active state, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

signal.

Claim 19 (original):. The programmable frequency divider of claim 17 further comprising:

5 at least one cell of a third type having a bypass mode and being cascaded between at least one cell of the first type and the cell of the second type, each cell of the third type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (Rs), a fifth input node (Ci), a first
10 output node (Fo), a second output node (Mo), and a third output node (Co), the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell of the third type, the third input node (Di)
15 being used for receiving a corresponding divisor signal, the fourth input node (Rs) being used for receiving the reset signal to synchronously reset the third cell, the fifth input node (Ci) being coupled to a third output node (Co) of the subsequent cell and being used for receiving a bypass-mode enabling
20 signal, a first input node (Fi) of a first cell of the third type being coupled to a first output node (Fo) of the last cell of the first type, a second output node (Mo) of the first cell of the third type being coupled to the second input node (Mi) of the last cell of the first type, a first output node (Fo) of a last cell
25 of the third type being coupled to the first input node (Fi) of the cell of the second type, a second input node (Mi) of the last cell of the third type being coupled to the second output node (Mo) of the cell of the second type;

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 wherein each cell of the third type switches to a divide-by-two or divide-by-three mode according to the divisor signal received on the third input node (Di), and if the bypass-mode enabling signal received on the fifth input node (Ci) is at an active state, the cell of the third type switches to a bypass mode.

Claim 20 (original): The programmable frequency divider of claim 19 wherein each cell of the third type operates such that:

- 10 (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) and the third input node (Di) are both at logic 0, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 15 (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a
- 20 one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- 25 (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal;
- (e) if the reset signal received on the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

and the second output node (Mo) outputs a logic 1 signal;
and

- (f) if the bypass-mode enabling signal received on the fifth
input node (Ci) is at an active state, the first output node
(Fo) outputs a logic 0 signal and the second output node
(Mo) outputs a logic 1 signal.

Claim 21 (original): The programmable frequency divider of claim 14
further comprising a control circuit for providing the reset
signal.

Claim 22 (cancelled)

Claim 23 (previously presented): A programmable frequency divider for
dividing the frequency of a source signal according to a
selectable divisor which is obtained based on a plurality of
divisor signals and outputting a result signal having a divided
frequency, the programmable frequency divider comprising:
at least one cell of a fourth type being switchable between
divide-by-two and divide-by-three modes having a first input
node (Fi), a second input node (Mi), a third input node (Di), a
fourth input node (Ri), a first output node (Fo), and a second
output node (Mo), the third input node (Di) being used for
receiving a corresponding divisor signal; the fourth input node
(Ri) being used for receiving a reload signal to synchronously
reload the corresponding divisor signal to the third input node
(Di);
wherein if the programmable frequency divider comprising a

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 plurality of cells of the fourth type, the cells of the fourth type
being cascaded with each other, the first output node (Fo)
being coupled to a first input node (Fi) of a subsequent cell of
the fourth type, the second input node (Mi) being coupled to a
second output node (Mo) of the subsequent cell of the fourth
type, a first input node (Fi) of a first cell of the fourth type
being coupled to the source signal, and a second input node
(Mi) of a last cell of the fourth type being set to logic 1; the
programmable frequency divider synchronously reloads the
10 corresponding divisor signals to the third input node (Di) of
each cell of the fourth type according to the reload signal in
order to selectively switch each cell of the fourth type to
perform a divide-by-two or divide-by-three operation, and the
second output node (Mo) or the first output node (Fo) of the
15 last cell of the fourth type outputs the result signal having the
divided frequency; and each cell of the fourth type operates
such that:

- 20 (a) regardless of the logic level of the second input node (Mi),
if the first output node (Fo) is at logic 0 and the third input
node (Di) is at logic 0 when the fourth input node (R1) is
triggered by the reload signal, the positive edge of a clock
signal of the first input node (Fi) triggers the first output
node (Fo) to output a half frequency signal;
- 25 (b) if the second input node (Mi) is at logic 1, the first output
node (Fo) is at logic 0, and the third input node (Di) is at
logic 1 when the fourth input node (R1) is triggered by the
reload signal, the positive edge of a clock signal of the first
input node (Fi) triggers the first output node (Fo) to output a

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

one-third-frequency signal;

(c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi); and

5 (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal.

10 Claim 24 (previously presented): A programmable frequency divider for dividing the frequency of a source signal according to a selectable divisor which is obtained based on a plurality of divisor signals and outputting a result signal having a divided frequency, the programmable frequency divider comprising:
15 at least one cell of a fourth type being switchable between divide-by-two and divide-by-three modes having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (Ri), a first output node (Fo), and a second output node (Mo), the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (Ri) being used for receiving a reload signal to synchronously
20 reload the corresponding divisor signal to the third input node (Di);

25 wherein if the programmable frequency divider comprising a plurality of cells of the fourth type, the cells of the fourth type being cascaded with each other, the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell of the fourth type, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell of the fourth

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 type, a first input node (Fi) of a first cell of the fourth type
being coupled to the source signal, and a second input node
(Mi) of a last cell of the fourth type being set to logic 1; the
programmable frequency divider synchronously reloads the
corresponding divisor signals to the third input node (Di) of
each cell of the fourth type according to the reload signal in
order to selectively switch each cell of the fourth type to
perform a divide-by-two or divide-by-three operation, the
10 second output node (Mo) or the first output node (Fo) of the
last cell of the fourth type outputs the result signal having the
divided frequency; and each cell of the fourth type operates
such that:

- 15 (a) regardless of the logic level of the second output node (Mo),
if the third input node (Di) is at logic 0 when the fourth
input node (Ri) is triggered by the reload signal, the
positive edge of a clock signal of the first input node (Fi)
triggers the first output node (Fo) to output a half frequency
signal;
- 20 (b) if the second output node (Mo) is at logic 1 and the third
input node (Di) is at logic 1 when the fourth input node (Ri)
is triggered by the reload signal, the positive edge of a clock
signal of the first input node (Fi) triggers the first output
node (Fo) to output a one-third-frequency signal;
- 25 (c) if the first output node (Fo) is at logic 0, the second output
node (Mo) outputs a signal at the same logic level as the
second input node (Mi); and
- (d) regardless of the logic level of the second input node (Mi),
if the first output node (Fo) is at logic 1, the second output

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

node (Mo) outputs a logic 0 signal.

5 Claim 25 (previously presented): A programmable frequency divider for
dividing the frequency of a source signal according to a
selectable divisor which is obtained based on a plurality of
divisor signals and outputting a result signal having a divided
frequency, the programmable frequency divider comprising:
at least one cell of a fourth type being switchable between
divide-by-two and divide-by-three modes having a first input
10 node (Fi), a second input node (Mi), a third input node (Di), a
fourth input node (Ri), a first output node (Fo), and a second
output node (Mo), the third input node (Di) being used for
receiving a corresponding divisor signal, the fourth input node
(Ri) being used for receiving a reload signal to synchronously
15 reload the corresponding divisor signal to the third input node
(Di), and the fourth input node (Ri) of each cell of the fourth
type is being coupled to a second output node (Mo) of the last
cell of the fourth type in order to apply the result signal having
the divided frequency to be the reload signal;
20 wherein if the programmable frequency divider comprising a
plurality of cells of the fourth type, the cells of the fourth type
being cascaded with each other, the first output node (Fo)
being coupled to a first input node (Fi) of a subsequent cell of
the fourth type, the second input node (Mi) being coupled to a
25 second output node (Mo) of the subsequent cell of the fourth
type, a first input node (Fi) of a first cell of the fourth type
being coupled to the source signal, and a second input node
(Mi) of a last cell of the fourth type being set to logic 1; the

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 programmable frequency divider synchronously reloads the corresponding divisor signals to the third input node (Di) of each cell of the fourth type according to the reload signal in order to selectively switch each cell of the fourth type to perform a divide-by-two or divide-by-three operation, and the second output node (Mo) or the first output node (Fo) of the last cell of the fourth type outputs the result signal having the divided frequency.

10 Claim 26 (previously presented): The programmable frequency divider of claim 25 further comprising:

15 a cell of a fifth type having a bypass mode and being cascaded to the last cell of the fourth type, the cell of the fifth type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (RI), a fifth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first input node (Fi) being coupled to a first output node (Fo) of the last cell of the fourth type, the second input node (Mi) being coupled to Vcc, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (RI) being used for receiving the reload signal to synchronously reload the corresponding divisor signal to the third input node (Di), the fifth input node (Ci) being coupled to the last divisor signal, and the second output node (Mo) being coupled to the second input node (Mi) of the last cell of the fourth type;

25 wherein the reload signal triggers the cell of the fifth type to synchronously reload the corresponding divisor signal to the

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

third input node (Di) and the cell of the fifth type switches to a divide-by-two or divide-by-three mode according to the divisor signal, and if the last divisor signal received in the fifth input node (Ci) is at a bypass-mode active state, the cell of the fifth type switches to a bypass mode.

Claim 27 (original): The programmable frequency divider of claim 26 wherein each cell of the fifth type operates such that:

- (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) is at logic 0 and the third input node (Di) is at logic 0 when the fourth input node (Rl) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1 when the fourth input node (Rl) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

(e) if the signal received in the fifth input node (Ci) is at an active state, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal.

5 Claim 28 (original): The programmable frequency divider of claim 26, wherein the fourth input node (R1) of the cell of the fifth type is coupled to the second output node (Mo) of the last cell of the fourth type in order to apply the result signal having the divided frequency to be the reload signal.

10

Claim 29 (original): The programmable frequency divider of claim 26, further comprising:

15

at least one cell of a sixth type having a bypass mode and being cascaded between at least one cell of the fourth type and the cell of the fifth type, each cell of the sixth type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (R1), a fifth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (R1) being used for receiving the reload signal to synchronously reload the the corresponding divisor signal to the third input node (Di), the fifth input node (Ci) being coupled to a third output node (Co) of the subsequent cell and being used for receiving a bypass-mode enabling signal, a first

20

25

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 input node (Fi) of a first cell of the sixth type being coupled to the first output node (Fo) of the last cell of the fourth type, a second output node (Mo) of the first cell of the sixth type being coupled to the second input node (Mi) of the last cell of the fourth type, a first output node (Fo) of a last cell of the sixth type being coupled to the first input node (Fi) of the cell of the fifth type, and a second input node (Mi) of the last cell of the sixth type being coupled to the second output node (Mo) of the cell of the fifth type;

10 wherein the reload signal triggers the at least one cell of the sixth type to synchronously reload the corresponding divisor signal to the third input node (Di) and each cell of the sixth type switches to a divide-by-two or divide-by-three mode according to the respective divisor signal, and if the

15 bypass-mode enabling signal received in the fifth input node (Ci) is at an active state, the cell of the sixth type switches to a bypass mode.

Claim 30 (original): The programmable frequency divider of claim 29,

20 wherein each cell of the sixth type operates such that:

(a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) is at logic 0 and the third input node (Di) is at logic 0 when the fourth input node (Ri) is triggered by the reload signal,

25 the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;

(b) if the first output node (Fo) is at logic 0, the second input

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

- 5 node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1 when the fourth input node (Ri) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal having the same logic level as the second input node (Mi);
- 10 (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and
- (e) if the bypass-mode enabling signal received on the fifth input node (Ci) is at an active state, the first output node
- 15 (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal.

Claim 31 (original): The programmable frequency divider of claim 29, wherein the fourth input node (Ri) of each cell of the sixth type

20 is coupled to the second output node (Mo) of the last cell of the fourth type in order to apply the result signal having the divided frequency to be the reload signal.

Claim 32 (original): A programmable frequency divider for dividing the

25 frequency of a source signal according to a selectable divisor which is obtained based on a plurality of divisor signals and outputting a result signal having a divided frequency, the programmable frequency divider comprising:

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 at least one cell of a seventh type being switchable between
divide-by-two and divide-by-three modes having a first input
node (Fi), a second input node (Mi), a third input node (Di), a
fourth input node (Rs), a fifth input node (Rl), a first output
node (Fo), and a second output node (Mo), the third input node
10 (Di) being used for receiving a corresponding divisor signal,
the fourth input node (Rs) being used for receiving a reset
signal to synchronously reset the cell of the seventh type, the
fifth input node (Rl) being used for receiving a reload signal to
synchronously reload the corresponding divisor signal to the
third input node (Di);
15 wherein if the programmable frequency divider comprising a
plurality of cells of the seventh type, the cells of the seventh
type being cascaded with each other and each cell of the
seventh type, the first output node (Fo) being coupled to a first
input node (Fi) of a subsequent cell of the seventh type, the
second input node (Mi) being coupled to a second output node
20 (Mo) of the subsequent cell of the seventh type, a first input
node (Fi) of a first cell of the seventh type being coupled to
the source signal, and a second input node (Mi) of a last cell of
the seventh type being set to logic 1; the programmable
frequency divider reloads the corresponding divisor signal to
the third input node (Di) of each cell of the seventh type
25 according to the reload signal and resets each cell of the
seventh type according to the reset signal in order to
selectively switch each cell of the seventh type to perform a
divide-by-two or divide-by-three operation according to the
respective divisor signal loaded before reset, and the second

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

output node (Mo) or the first output node (Fo) of the last cell of the seventh type outputs the result signal having the divided frequency.

- 5 Claim 33 (original): The programmable frequency divider of claim 32, wherein each cell of the seventh type operates such that:
- 10 (a) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 0 and the third input node (Di) is at logic 0 when the fifth input node (RI) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
 - 15 (b) if the second input node (Mi) is at logic 1, the first output node (Fo) is at logic 0, and the third input node (Di) is at logic 1 when the fifth input node (RI) is triggered by the reload signal, the positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
 - 20 (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
 - (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and
 - 25 (e) if the reset signal received on the fourth input node (Rs) is at logic 1, the first output node (Fo) outputs a logic 0 signal; and, additionally, if the second input node (Mi) is also at logic 1, the second output node (Mo) outputs a logic 1

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

signal.

Claim 34 (original): The programmable frequency divider of claim 32, wherein each cell of the seventh type operates such that:

- 5 (a) regardless of the logic level of the second output node (Mo), if the third input node (Di) is at logic 0 when the fifth input node (Rl) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 10 (b) if the second output node (Mo) is at logic 1 and the third input node (Di) is at logic 1 when the fifth input node (Rl) is triggered by the reload signal, the positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- 15 (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic signal as the second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output
20 node (Mo) outputs a logic 0 signal; and
- (e) if the reset signal received on the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal; and, additionally, if the second input node (Mi) is also at
25 logic 1, the second output node (Mo) outputs a logic 1 signal.

Claim 35 (original): The programmable frequency divider of claim 32, wherein the fifth input node (Rl) of each cell of the seventh type

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

is coupled to the second output node (Mo) of the last cell of the seventh type in order to apply the result signal to be the reload signal.

- 5 Claim 36 (original): The programmable frequency divider of claim 32, further comprising a control circuit for providing the reset signal.

- 10 Claim 37 (original): The programmable frequency divider of claim 32, further comprising:

 a cell of an eighth type having a bypass mode and being cascaded to the last cell of the seventh type, the cell of the eighth type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (Rs), a fifth
15 input node (Rl), a sixth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first input node (Fi) being coupled to a first output node (Fo) of the last cell of the seventh type, the second input node (Mi) being coupled to Vcc, the third input node (Di) being
20 used for receiving a corresponding divisor signal, the fourth input node (Rs) being used for receiving the reset signal to reset the cell of the eighth type, the fifth input node (Rl) being used for receiving the reload signal to synchronously reload the corresponding divisor signal to the third input node (Di),
25 the sixth input node (Ci) being coupled to the last divisor signal, and the second output node (Mo) being coupled to the second input node (Mi) of the last cell of the seventh type;
 wherein the reload signal triggers the cell of the eighth type to

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

synchronously reload the corresponding divisor signal to the third input node (Di) and the cell of the eighth type switches to a divide-by-two or a divide-by-three mode after being synchronously reset according to the divisor signal, and if the last divisor signal received on the sixth input node (Ci) is at a bypass-mode active state, the cell of the eighth type switches to a bypass mode.

Claim 38 (original): The programmable frequency divider of claim 37, wherein each cell of the eighth type operates such that:

- (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) is at logic 0, and the third input node (Di) is at logic 0 when the fifth input node (Ri) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1 when the fifth input node (Ri) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi),

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

- if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal;
- 5 (e) if the reset signal received on the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal; and
- (f) if the signal received on the sixth input node (Ci) is at an active state, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal.
- 10

Claim 39 (original): The programmable frequency divider of claim 37, wherein the fifth input node (R1) is coupled to the second output node (Mo) of the last cell of the seventh type in order to apply the result signal to be the reload signal.

15

Claim 40 (original): The programmable frequency divider of claim 37, further comprising:

20 at least one cell of a ninth type having a bypass mode and being cascaded between at least one cell of the seventh type and the cell of the eighth type, each cell of the ninth type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (Rs), a fifth input node (R1), a sixth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell of the ninth type, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell,

25

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 the third input node (Di) being used for receiving a
corresponding divisor signal, the fourth input node (Rs) being
used for receiving the reset signal to synchronously reset the
cell of the ninth type, the fifth input node (Rl) being used for
receiving the reload signal to synchronously reload the
corresponding divisor signal to the third input node (Di), the
sixth input node (Ci) being coupled to a third output node (Co)
of the subsequent cell and being used for receiving a
bypass-mode enabling signal, a first input node (Fi) of a first
10 cell of the ninth type being coupled to the first output node (Fo)
of the last cell of the seventh type, a second output node (Mo)
of the first cell of the ninth type being coupled to the second
input node (Mi) of the last cell of the seventh type, a first
output node (Fo) of a last cell of the ninth type being coupled
15 to the first input node (Fi) of the cell of the eighth type, and a
second input node (Mi) of the last cell of the ninth type being
coupled to the second output node (Mo) of the cell of the
eighth type;
wherein the reload signal triggers the at least one cell of the
20 ninth type to synchronously reload the corresponding divisor
signal to the third input node (Di) and each cell of the ninth
type switches to a divide-by-two or divide-by-three mode after
being synchronously reset according to the respective divisor
signal, and if the bypass-mode enabling signal received on the
25 sixth input node (Ci) is at an active state, the cell of the ninth
type switches to a bypass mode.

Claim 41 (original): The programmable frequency divider of claim 40,

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

wherein each cell of the ninth type operates such that:

- 5 (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) is at logic 0 and the third input node (Di) is at logic 0 when the fifth input node (Ri) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 10 (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1 when the fifth input node (Ri) triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a
- 15 one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- 20 (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal;
- (e) if the reset signal received on the fourth input node (Rs) is enabled, the first output node (Fo) outputs a logic 0 signal; and, additionally, if the second input node (Mi) is also at
- 25 logic 1, the second output node (Mo) outputs a logic 1 signal; and
- (f) if the bypass-mode enabling signal received on the sixth input node (Ci) is at an active state, the first output node

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

(Fo) outputs a logic 0 signal and the second output node
(Mo) outputs a logic 1 signal.

5 Claim 42 (original): The programmable frequency divider of claim 40,
wherein the fifth input node (RI) of each cell of the ninth type is
coupled to the second output node (Mo) of the last cell of the
seventh type in order to apply the result signal to be the reload
signal.

10 Claim 43 (cancelled)

Claim 44 (previously presented): A programmable frequency divider for
dividing frequency of a source signal according to a selectable
divisor which is obtained based on a plurality of divisor signals
15 and outputting a result signal having a divided frequency, the
programmable frequency divider comprising:
at least one cell of a tenth type being switchable between
divide-by-two and divide-by-three modes having a first input
node (Fi), a second input node (Mi), a third input node (Di), a
20 first output node (Fo), and a second output node (Mo), the
third input node (Di) being used for receiving a corresponding
divisor signal, and the first input node (Fi) of a first cell of the
tenth type being coupled to the source signal; and
a cell of an eleventh type having a first input node (Fi), a second
25 input node (Mi), a third input node (Di), a fourth input node
(RI), a fifth input node (Ci), a first output node (Fo), a second
output node (Mo), and a third output node (Co), the first input
node (Fi) being coupled to a first output node (Fo) of a last

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 cell of the tenth type, the second input node (Mi) being set to logic 1, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (Ri) being used for receiving a reload signal to synchronously reload the corresponding divisor signal to the third input node (Di), the fifth input node (Ci) being coupled to a last divisor signal, and the second output node (Mo) being coupled to a second input node (Mi) of the last cell of the tenth type;

10 wherein if the programmable frequency divider comprising a plurality of cells of the tenth type, the cells of the tenth type being cascaded with each other and each cell of the tenth type, the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell of the tenth type, the second input node (Mi) being coupled to a second output node (Mo) of the
15 subsequent cell of the tenth type; the programmable frequency divider selectively switches each cell to a divide-by-two or a divide-by-three mode according to the respective divisor signal, the reload signal triggers the third input node (Di) of the cell of the eleventh type to reload the corresponding
20 divisor signal, if the last divisor signal received in the fifth input node (Ci) of the cell of the eleven type is at a bypass-mode active state, the cell of the eleventh type switches to a bypass mode, and the second output node (Mo) or the first output node (Fo) of the last cell of the tenth type
25 outputs the result signal having the divided frequency; each cell of the tenth type operates such that:

- (a) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 0 and the third input

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

node (Di) is at logic 0, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;

5 (b) if the second input node (Mi) is at logic 1, the first output node (Fo) is at logic 0, and the third input node (Di) is at logic 1, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;

10 (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi); and

(d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal.

15 Claim 45 (previously presented): A programmable frequency divider for dividing frequency of a source signal according to a selectable divisor which is obtained based on a plurality of divisor signals and outputting a result signal having a divided frequency, the
20 programmable frequency divider comprising:

at least one cell of a tenth type being switchable between divide-by-two and divide-by-three modes having a first input node (Fi), a second input node (Mi), a third input node (Di), a first output node (Fo), and a second output node (Mo), the
25 the third input node (Di) being used for receiving a corresponding divisor signal, and the first input node (Fi) of a first cell of the tenth type being coupled to the source signal; and
a cell of an eleventh type having a first input node (Fi), a second

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

5 input node (Mi), a third input node (Di), a fourth input node (RI), a fifth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first input node (Fi) being coupled to a first output node (Fo) of a last cell of the tenth type, the second input node (Mi) being set to logic 1, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (RI) being used for receiving a reload signal to synchronously reload the corresponding divisor signal to the third input node (Di), the 10 fifth input node (Ci) being coupled to a last divisor signal, and the second output node (Mo) being coupled to a second input node (Mi) of the last cell of the tenth type;

15 wherein if the programmable frequency divider comprising a plurality of cells of the tenth type, the cells of the tenth type being cascaded with each other and each cell of the tenth type, the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell of the tenth type, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell of the tenth type; the programmable frequency divider selectively switches each cell to a divide-by-two or a divide-by-three mode according to the respective divisor signal, the reload signal triggers the third input node (Di) of the cell of the eleventh type to reload the corresponding divisor signal, if the last divisor signal received in the fifth input node (Ci) of the cell of the eleven type is at a bypass-mode active state, the cell of the eleventh type switches to a bypass mode, and the second output node (Mo) or the first output node (Fo) of the last cell of the tenth type

20

25

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

outputs the result signal having the divided frequency; each cell of the tenth type operates such that:

- 5 (a) regardless of the logic level of the second output node (Mo), if the third input node (Di) is at logic 0, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 10 (b) if the second output node (Mo) and the third input node (Di) are both at logic 1, the positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi); and
- 15 (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal.

Claim 46 (previously presented): A programmable frequency divider for dividing frequency of a source signal according to a selectable divisor which is obtained based on a plurality of divisor signals and outputting a result signal having a divided frequency, the programmable frequency divider comprising:

20

at least one cell of a tenth type being switchable between divide-by-two and divide-by-three modes having a first input node (Fi), a second input node (Mi), a third input node (Di), a first output node (Fo), and a second output node (Mo), the third input node (Di) being used for receiving a corresponding divisor signal, and the first input node (Fi) of a first cell of the

25

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

tenth type being coupled to the source signal; and
a cell of an eleventh type having a first input node (Fi), a second
input node (Mi), a third input node (Di), a fourth input node
(Ri), a fifth input node (Ci), a first output node (Fo), a second
5 output node (Mo), and a third output node (Co), the first input
node (Fi) being coupled to a first output node (Fo) of a last
cell of the tenth type, the second input node (Mi) being set to
logic 1, the third input node (Di) being used for receiving a
corresponding divisor signal, the fourth input node (Ri) being
10 used for receiving a reload signal to synchronously reload the
corresponding divisor signal to the third input node (Di), the
fifth input node (Ci) being coupled to a last divisor signal, and
the second output node (Mo) being coupled to a second input
node (Mi) of the last cell of the tenth type;
15 wherein if the programmable frequency divider comprising a
plurality of cells of the tenth type, the cells of the tenth type
being cascaded with each other and each cell of the tenth type,
the first output node (Fo) being coupled to a first input node
(Fi) of a subsequent cell of the tenth type, the second input
20 node (Mi) being coupled to a second output node (Mo) of the
subsequent cell of the tenth type; the programmable frequency
divider selectively switches each cell to a divide-by-two or a
divide-by-three mode according to the respective divisor
signal, the reload signal triggers the third input node (Di) of
25 the cell of the eleventh type to reload the corresponding
divisor signal, if the last divisor signal received in the fifth
input node (Ci) of the cell of the eleven type is at a
bypass-mode active state, the cell of the eleventh type

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

switches to a bypass mode, and the second output node (Mo) or the first output node (Fo) of the last cell of the tenth type outputs the result signal having the divided frequency;-the cell of the eleventh type operates such that:

- 5 (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) is at logic 0 and the third input node (Di) is at logic 0 when the fourth input node (Rl) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi)
- 10 triggers the first output node (Fo) to output a half frequency signal;
- (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1 when
- 15 the fourth input node (Rl) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the
- 20 second input node (Mi);
- (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and
- 25 (e) if the signal received on the fifth input node (Ci) is at an active state, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal.

Appl. No. 10/711,410
Amtd. dated January 22, 2007
Reply to Office action of October 23, 2006

Claim 47 (previously presented): A programmable frequency divider for dividing frequency of a source signal according to a selectable divisor which is obtained based on a plurality of divisor signals and outputting a result signal having a divided frequency, the
5 programmable frequency divider comprising:
at least one cell of a tenth type being switchable between divide-by-two and divide-by-three modes having a first input node (Fi), a second input node (Mi), a third input node (Di), a
10 first output node (Fo), and a second output node (Mo), the third input node (Di) being used for receiving a corresponding divisor signal, and the first input node (Fi) of a first cell of the tenth type being coupled to the source signal; and
a cell of an eleventh type having a first input node (Fi), a second
15 input node (Mi), a third input node (Di), a fourth input node (Ri), a fifth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first input node (Fi) being coupled to a first output node (Fo) of a last cell of the tenth type, the second input node (Mi) being set to
20 logic 1, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (Ri) being used for receiving a reload signal to synchronously reload the corresponding divisor signal to the third input node (Di), the fifth input node (Ci) being coupled to a last divisor signal, the
25 second output node (Mo) being coupled to a second input node (Mi) of the last cell of the tenth type; and the fourth input node (Ri) is being coupled to the second output node (Mo) of the last cell of the tenth type in order to apply the result signal to

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

be the reload signal;
wherein if the programmable frequency divider comprising a plurality of cells of the tenth type, the cells of the tenth type being cascaded with each other and each cell of the tenth type, the first output node (Fo) being coupled to a first input node (Fi) of a subsequent cell of the tenth type, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell of the tenth type; the programmable frequency divider selectively switches each cell to a divide-by-two or a divide-by-three mode according to the respective divisor signal, the reload signal triggers the third input node (Di) of the cell of the eleventh type to reload the corresponding divisor signal, if the last divisor signal received in the fifth input node (Ci) of the cell of the eleven type is at a bypass-mode active state, the cell of the eleventh type switches to a bypass mode, and the second output node (Mo) or the first output node (Fo) of the last cell of the tenth type outputs the result signal having the divided frequency.

Claim 48 (previously presented): The programmable frequency divider of claim 47, further comprising:
at least one cell of a twelfth type being cascaded between at least one cell of the tenth type and the cell of the eleventh type, and each cell of the twelfth type having a first input node (Fi), a second input node (Mi), a third input node (Di), a fourth input node (Ri), a fifth input node (Ci), a first output node (Fo), a second output node (Mo), and a third output node (Co), the first output node (Fo) being coupled to a first input node

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

(Fi) of a subsequent cell of the twelfth type, the second input node (Mi) being coupled to a second output node (Mo) of the subsequent cell, the third input node (Di) being used for receiving a corresponding divisor signal, the fourth input node (Ri) being used for receiving the reload signal to synchronously reload the corresponding divisor signal to the third input node (Di), the fifth input node (Ci) being coupled to a third output node (Co) of the subsequent cell and being used for receiving a bypass-mode enabling signal, a first input node (Fi) of a first cell of the twelfth type being coupled to the first output node (Fo) of the last cell of the tenth type, a second output node (Mo) of the first cell of the twelfth type being coupled to the second input node (Mi) of the last cell of the tenth type, a first output node (Fo) of a last cell of the twelfth type being coupled to the first input node (Fi) of the cell of the eleventh type, and a second input node (Mi) of the last cell of the twelfth type being coupled to the second output node (Mo) of the cell of the eleventh type;

wherein the reload signal triggers each cell of the twelfth type to synchronously reload the corresponding divisor signal to the third input node (Di), each cell of the twelfth type switches to a divide-by-two or divide-by-three mode according to the loaded divisor signal, and if the bypass-mode enabling signal received on the fifth input node (Ci) is at an active state, the cell of the twelfth type switches to a bypass mode.

Claim 49 (original): The programmable frequency divider of claim 48, wherein each cell of the twelfth type operates such that:

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

- 5 (a) regardless of the logic level of the second input node (Mi) or the second output node (Mo), if the first output node (Fo) is at logic 0 and the third input node (Di) is at logic 0 when the fourth input node (Rl) is triggered by the reload signal, the positive edge of a clock signal of the first input node (Fi) triggers the first output node (Fo) to output a half frequency signal;
- 10 (b) if the first output node (Fo) is at logic 0, the second input node (Mi) is at logic 1 (or if the second output node (Mo) is at logic 1), and the third input node (Di) is at logic 1 when the fourth input node (Rl) is triggered by the reload signal, the positive edge of the clock signal of the first input node (Fi) triggers the first output node (Fo) to output a one-third-frequency signal;
- 15 (c) if the first output node (Fo) is at logic 0, the second output node (Mo) outputs a signal at the same logic level as the second input node (Mi);
- 20 (d) regardless of the logic level of the second input node (Mi), if the first output node (Fo) is at logic 1, the second output node (Mo) outputs a logic 0 signal; and
- 25 (e) if the bypass-mode enabling signal received on the fifth input node (Ci) is at an active state, the first output node (Fo) outputs a logic 0 signal and the second output node (Mo) outputs a logic 1 signal.

Claim 50 (original): The programmable frequency divider of claim 48, wherein the fourth input node (Rl) of each cell of the twelfth type is coupled to the second output node (Mo) of the last cell of

Appl. No. 10/711,410
Amdt. dated January 22, 2007
Reply to Office action of October 23, 2006

the tenth type in order to apply the result signal to be the reload
signal.

5 Claim 51 (new): The method of claim 3, wherein step (c) further comprises
 reloading the plurality of divisor signals to the plurality of cells
 in response to the reset signal.